

Total No. of Questions : 8]

P2950

SEAT No. :

[Total No. of Pages : 2

[5669]-539

T.E. (Electrical)

### DESIGN OF ELECTRICAL MACHINES

(2015 Pattern) (Semester - II)

Time : 2½ Hours]

[Max. Marks : 70

Instructions to the candidates:

- 1) Solve Q1 or Q2, Q3 or Q4, Q5 or Q6, Q7 or Q8.
- 2) Neat diagrams must be drawn wherever necessary.
- 3) Figures to the right indicates full marks.
- 4) Use of Calculator is allowed.
- 5) Assume Suitable data if necessary.

- Q1)** a) Derive the output equation for a three phase core type transformer. [6]  
b) Explain the different modes of heat dissipation. [6]  
c) Explain the mechanical forces developed under short circuit conditions. [8]  
Also state the measures to overcome this effect.

OR

- Q2)** a) Explain any three types of windings used in a transformer. [6]  
b) Explain the procedure to calculate the no load current in case of a three phase transformer. [6]  
c) Explain the procedure for the design of tank with tubes and derive the relation for the number of tubes. [8]

- Q3)** a) Define specific electrical and magnetic loadings. Explain the factors to be considered for the choice of specific electrical loading and specific magnetic loading. [8]  
b) Derive the Output equation for three phase induction motor with usual notations. [8]

OR

- Q4)** a) Explain the design of any two types of AC windings. [8]  
b) Explain the various factors in detail which play a major role while deciding the number of stator slots. [8]

- Q5)** a) What are the suitable combinations of designing stator and rotor slots? [8]  
b) Derive the equation for end ring current for the rotor of squirrel cage induction motor. [8]

P.T.O.

OR

- Q6)** a) Explain the various factors which affect the length of air gap in an induction motor. [8]

- b) A 11 KW, 220 V, 3-phase, 6 pole, star connected squirrel cage induction motor has the following data : number of stator slots = 54, number of conductor in each stator slot = 9, number of rotor bars = 64, efficiency = 0.86, power factor = 0.85, current density = 5A/mm<sup>2</sup>. Find bar current, end ring current, area of bar, area of end ring. Assume Rotor mmf as 85% of Stator mmf. Assume suitable data if required. [8]

- Q7)** a) Explain [6]

i) Slot leakage

ii) Tooth top leakage

iii) Zig-zag leakage

iv) Overhang leakage with the help of necessary diagrams.

- b) Explain the effects of ducts on calculation of magnetizing current. [6]

- c) A 75KW, 3300V, 50 Hz, 8 pole, 3 phase, star connected induction motor has a magnetizing current which is 40% of full load current. Calculate the value of stator turns per phase if the mmf required for flux density at 60° from the pole axis is 500A, winding factor 0.95, efficiency = 0.94 and power factor = 0.86. Assume suitable data if required. [6]

OR

- Q8)** a) Explain the MMF Calculation for air gap, stator teeth, stator core, rotor teeth and rotor core. [6]

- b) Explain how the no load current is calculated in case of induction motor. [6]

- c) Calculate the magnetizing current for 415 V, 3-phase, 50 Hz, 4 pole induction motor which has the following dimensions: air gap length is 0.5mm; flux density at 60° is 0.478 wb/m<sup>2</sup>. The stator winding is delta connected with 4 slots / pole / phase and 28 conductors / slot. The ampere turns for the iron path is equal to 45% of the air gap ampere turns. Assume the gap contraction factor as 1.2, stator winding factor = 0.955. Assume suitable data if required. [6]



[5669]-539